

This Page Is Inserted by IFW Operations  
and is not a part of the Official Record

## **BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

**IMAGES ARE BEST AVAILABLE COPY.**

**As rescanning documents *will not* correct images,  
please do not report the images to the  
Image Problem Mailbox.**

**TITLE**

**APPARATUS AND METHOD FOR DETECTING AN ABNORMALITY IN  
A RECORDED SIGNAL**

**BACKGROUND OF THE INVENTION**

**Technical Field**

**[0001]** The present invention relates to an apparatus and process for detecting an abnormality in a recorded signal, and, more particularly, to apparatus and processes for detecting abnormalities in recorded signals during the recording of the signal onto a recording medium.

**Related Art**

**[0002]** Generally, a digital magnetic recorder/player such as a digital video cassette (DVC), or the like, records and reproduces a digital signal, with advantages of higher quality of image and sound over an analog type signal, and also an easier editing process. The digital magnetic recorder/player generally uses a magnetic tape as a recording medium for storing the digital data of image and sound. Heads are formed on a rotary head drum of the recorder/player to record and reproduce signals on and from the magnetic tape.

**[0003]** During the use of the recorder/player, possibility is high that foreign substances are

1 transferred from the magnetic tape to the head. Another high possibility is that foreign  
2 substances, floating in air, can be attached to the surface of the head. In the event that foreign  
3 substances are attached to the surface of the head, malfunction occurs in recording or  
4 reproducing process, causing undesired and abnormal signal recording or reproducing. In order  
5 to eliminate the foreign substances, a foreign substance cleaning tape is used, and sometimes, a  
6 user eliminates the foreign substances manually.

7 [0004] The source of abnormal recording/reproducing comes not only from the presence of  
8 foreign substances on the surface of the head, but also from problems associated with the head  
9 itself, or the errors of peripheral circuits which supply recorded signal to the head. Whether the  
10 abnormal signal recording is caused by the presence of foreign substances on the head or from  
11 problems associated with the head or other devices, the overriding difficulty is that the user does  
12 not immediately learn about the presence of the abnormality because the user is not provided  
13 with any way to either detect the occurrence of the abnormality or to identify or otherwise locate  
14 the cause of the abnormality. Although a user could consider the quality of image and sound for  
15 determining abnormal signal recording through the user's anatomical audio and visual senses  
16 during reproducing process, during the recording process, the user is not able to determine if the  
17 abnormal signal is being recorded or if the information that is being recording is not being  
18 recorded at all. As a result, the user usually keeps recording for a long period of time, only to  
19 find that all of the user's labors were a waste of time and effort. I have noticed that recording  
20 operations that produce errors or abnormalities can be extremely inconvenient; often the

1 recording efforts can not be recreated once the defective equipment has been repaired or  
2 replaced. Efforts have been made to improve recording technologies.

3 [0005] Exemplars of recent efforts in the art include U.S. Patent No. 6,141,486 for *METHODS*  
4 *AND APPARATUS FOR RECORDING DIGITAL DATA INCLUDING SYNC BLOCK AND*  
5 *TRACK NUMBER INFORMATION FOR USE DURING TRICK PLAY OPERATION* issued to  
6 Lane *et al.*, U.S. Patent No. 4,849,979 for *FAULT TOLERANT COMPUTER ARCHITECTURE*  
7 issued to Maccianti *et al.*, U.S. Patent No. 6,141,164 for *DATA RECORDING/REPRODUCING*  
8 *APPARATUS EMPLOYING READ-AFTER-WRITE SYSTEM* issued to Ishibashi *et al.*, U.S.  
9 Patent No. 6,134,384 for *DIGITAL SIGNAL RECORDING/REPRODUCING APPARATUS AND*  
10 *RECORDING METHOD* issued to Okamoto *et al.*, U.S. Patent No. 5,291,342 for  
11 *MULTIFUNCTIONAL CONTROL TYPE VIDEO HEAD SELECTING DEVICE AND METHOD*  
12 *THEREOF* issued to Kim, and U.S. Patent No. 6,163,421 for *AZIMUTH MAGNETIC*  
13 *RECORDING AND REPRODUCING APPARATUS AND METHOD EMPLOYING*  
14 *WAVEFORM EQUALIZATION* issued to Shinpuku *et al.* While these recent efforts provide  
15 advantages, I note that they fail to adequately provide an apparatus and method for efficiently and  
16 conveniently detecting abnormalities in recorded signals.

## 17 SUMMARY OF THE INVENTION

18 [0006] It is therefore, one object of the present invention to provide an improved process and  
19 apparatus for recording information.

1     **[0007]**     It is another object to provide a process and apparatus that enables a user to promptly  
2     detect the presence of abnormalities in information recorded onto a record medium.

3     **[0008]**     It is still another object to provide a process and apparatus that enables a user to  
4     promptly detect the occurrence of abnormalities during the recording of information onto a  
5     record medium.

6     **[0009]**     It is yet another object to provide an apparatus and process for detecting an abnormality  
7     of recorded signal of a digital magnetic recorder/player during a process of recording a signal on  
8     a magnetic tape, which is occurred when recording is abnormally performed by the presence of  
9     foreign substances on the head or by other problem sources.

10    **[0010]**    These and other objects may be attained with an apparatus for detecting an abnormality  
11    of a recorded signal of a digital magnetic recorder/player according to the present invention,  
12    including a plurality of heads for recording/reproducing a signal on/from a magnetic tape, a  
13    control portion for controlling the heads in such a manner that the signal, recorded by at least one  
14    head, is reproduced from the magnetic tape while the signal is recorded on the magnetic tape, and  
15    a determining portion for determining abnormality of recorded signal based on the signal  
16    reproduced from the magnetic tape.

17    **[0011]**    The determining portion determines the abnormality of recorded signal based on the  
18    fact whether or not a data format of at least a part of the signal reproduced from the magnetic  
19    tape is normal, and also determines malfunction of the heads based on a result obtained after  
20    comparing the signal reproduced from the magnetic tape with a reference signal.

1    **[0012]**     The plurality of heads include a first recording/reproducing head and a second  
2    recording/reproducing head disposed on opposite outer surfaces of a head drum, and a third  
3    reproducing/reproducing head disposed on the outer surface the head drum and between the first  
4    and second recording/reproducing heads. Preferably, the first and second recording/reproducing  
5    heads are used to record/reproduce data in a standard definition (SD) mode for  
6    recording/reproducing, and the third reproducing/reproducing head is used in a standard  
7    definition long-play (SDL) mode of the recording/reproducing and not used in the standard  
8    definition (SD) mode.

9    **[0013]**     According to the present invention, while the digital magnetic recorder/player performs  
10   recording, abnormality of recorded signal is detected by reproducing a signal from the magnetic  
11   tape just after the signal is recorded, and then inspecting the signal or comparing the signal with a  
12   reference signal. Also, especially when using the head, which is not used in a standard definition  
13   mode, for the purpose of detecting the abnormality of recorded signal, there is an advantage of  
14   not having to install an additional recording/reproducing head for detecting abnormality.

15   **[0014]**     Meanwhile, according to the present invention, there is provided a method for detecting  
16   an abnormality of recorded signal of a digital magnetic recorder/player, including the steps of  
17   recording a signal on a magnetic tape, reproducing the signal from the magnetic tape, and  
18   determining abnormality of recorded signal based on the signal reproduced from the magnetic  
19   tape.

1     **[0015]**     To achieve these and other objects in accordance with the principles of the present  
2     invention, as embodied and broadly described, the present invention provides an apparatus  
3     detecting abnormalities, said apparatus comprising: a plurality of heads recording data onto a  
4     medium and reproducing data from the medium; a controlling unit controlling said plurality of  
5     heads to reproduce a signal from the medium while the signal is being recorded onto the  
6     medium; and a determining unit determining an abnormality in the recorded signal in dependence  
7     upon the signal reproduced from the medium.

8     **[0016]**     To achieve these and other objects in accordance with the principles of the present  
9     invention, as embodied and broadly described, the present invention provides a method for  
10    detecting an abnormality of a recorded signal, comprising the steps of: recording a signal on a  
11    medium; reproducing the signal from the medium; and determining an abnormality of the  
12    recorded signal in dependence upon the signal reproduced from the medium.

13    **[0017]**     To achieve these and other objects in accordance with the principles of the present  
14    invention, as embodied and broadly described, the present invention provides an apparatus,  
15    comprising: a plurality of heads recording data onto a medium and reproducing data from the  
16    medium, said heads reproducing a signal from the medium while the signal is being recorded  
17    onto the medium; and a determining unit determining an abnormality in the recorded signal in  
18    dependence upon the signal reproduced from the medium.

1     **[0018]**     To achieve these and other objects in accordance with the principles of the present  
2     invention, as embodied and broadly described, the present invention provides a recording and  
3     reproducing apparatus, comprising: a controller outputting first and second switching signals; a  
4     first switch operating in response to said first switching signal, said operating of said first switch  
5     activating a first head to record first data onto a medium; and a second switch operating in  
6     response to said second switching signal, said operating of said second switch activating a second  
7     head to reproduce second data from the medium, said second data corresponding to said first data  
8     recorded on the medium; said reproducing of said second data being performed during said  
9     recording of said first data.

10    **[0019]**     To achieve these and other objects in accordance with the principles of the present  
11    invention, as embodied and broadly described, the present invention provides a recording and  
12    reproducing apparatus, comprising: a processor having an input terminal and an output terminal;  
13    said processor outputting a first data signal from said output terminal; and said processor  
14    receiving a second data signal at said input terminal during said outputting of said first data  
15    signal.

16    **[0020]**     The present invention is more specifically described in the following paragraphs by  
17    reference to the drawings attached only by way of example. Other advantages and features will  
18    become apparent from the following description and from the claims.



**BRIEF DESCRIPTION OF THE DRAWINGS**

[0021] A more complete appreciation of this invention, and many of the attendant advantages thereof, will be readily apparent as the same becomes better understood by reference to the following detailed description when considered in conjunction with the accompanying drawings in which like reference symbols indicate the same or similar components, wherein:

[0022] FIG. 1 is a schematic side view showing an arrangement of a head drum and a magnetic tape of a digital magnetic recorder/player;

[0023] FIG. 2 is an enlarged top view of FIG. 1;

[0024] FIGS. 3 and 4 are partial plan views showing the structure of the magnetic tape;

[0025] FIG. 5 is a block diagram of the digital magnetic recorder/player having an apparatus for detecting abnormality of recorded signal, in accordance with the principles of the present invention;

[0026] FIG. 6 is a detailed block diagram of a pre-amp shown in FIG. 5, constructed in accordance with the principles of the present invention;

[0027] FIG. 7 is a graph showing the switching timing of respective heads for detecting an abnormality of recorded signal, in accordance with the principles of the present invention;

[0028] FIGS. 8 to 11 are different views that sequentially show the variation of the position of the heads on the magnetic tape during an abnormality detection of recorded signal, in accordance with the principles of the present invention;

[0029] FIG. 12 is a flow chart for explaining a method for detecting abnormality of recorded signal according to a first preferred embodiment of the present invention;

1     **[0030]**     FIG. 13 is a flow chart that explains a method for detecting abnormality of recorded  
2     signal according to a second preferred embodiment of the present invention;

3     **[0031]**     FIG. 14 is a diagram for explaining the comparison performed by a microcomputer to  
4     determine if abnormalities exist in a recorded signal, in accordance with the principles of the  
5     present invention; and

6     **[0032]**     FIG. 15 is a diagram for explaining the function of the error check and compress  
7     system, in accordance with the principles of the present invention.

#### 8                   **DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS**

9     **[0033]**     While the present invention will be described more fully hereinafter with reference to  
10    the accompanying drawings, in which a preferred embodiment of the present invention is shown,  
11    it is to be understood at the outset of the description which follows that persons of skill in the  
12    appropriate art may modify the invention here described while still achieving the favorable  
13    results of this invention. Accordingly, the description which follows is to be understood as being  
14    a broad, teaching disclosure directed to persons of skill in the appropriate arts, and not as limiting  
15    upon the present invention.

16    **[0034]**     The present invention will be described in greater detail below with reference to the  
17    accompanying drawings. First, the structure of a general head drum and a magnetic tape will be  
18    described, and the description of the apparatus and method of the present invention will follow.  
19    Turning now to the drawings, FIGS. 1 and 2 schematically show the arrangement of the head

1 drum and the magnetic tape in a digital magnetic recorder/player. When a cassette, housing a roll  
2 of magnetic tape (not shown), is inserted in the digital magnetic recorder/player such as digital  
3 video cassette, or the like, as shown in FIG. 1, the magnetic tape 10 surrounds approximately a  
4 half of an outer circumference of the head drum 20. Next, when a motor (not shown) drives the  
5 cassette, the magnetic tape 10 in the cassette runs in a longitudinal direction thereof as indicated  
6 by the "tape running direction" arrow in FIG. 1. Simultaneously, the head drum 20 is rotated in  
7 the direction indicated by the "drum rotating direction" arrow by a drum motor (not shown).

8 [0035] The magnetic tape 10 includes a plurality of slant tracks 11 and 12 which are formed  
9 along the longitudinal direction thereof. As shown in FIG. 2, the slant tracks 11 and 12 are at a  
10 predetermined angle with respect to the longitudinal direction of the magnetic tape 10.

11 [0036] As shown in FIG. 2, the head drum 20 is disposed at a predetermined angle with  
12 respect to the longitudinal direction of the slant tracks 11 and 12. On the outer surface of the  
13 head drum 20, three heads, i.e., first, second, and third heads A, B, and C are installed.  
14 Generally, the first head is called a head A, the second head is called a head B, and the third head  
15 is called a head C, respectively. Heads A and B are disposed on the outer surface of the head  
16 drum 20, opposite to each other, that is, spaced from each other at an angle of 180 degrees  
17 (180°). The head C is disposed between the heads A and B in a manner of being spaced from the  
18 heads A and B at an angle of 90°.

1     **[0037]**   Heads A and B correspond to the second and first slant tracks 12 and 11, respectively.  
2     In other words, head B records and reproduces signal on and from the first slant tracks 11, while  
3     the head A records and reproduces the signal on and from the second slant tracks 12.

4     **[0038]**   During the rotation of the head drum 20 by 180°, the magnetic tape 10 runs a distance  
5     corresponding to the width of one track. When the head drum 20 is rotated, the magnetic tape 10  
6     is moved, and the head B, which is positioned at a lower end of the first slant track 11, moves  
7     along the first slant track 11. When the head B reaches an upper end of the first slant track 11,  
8     the head A is positioned at the lower end of the second slant track 12 next to the first slant track  
9     11. By repeating the above processes, the heads B and A sequentially record a signal onto, or  
10    reproduce a signal from, the first and second slant tracks 11 and 12 which are formed in an  
11    alternate fashion.

12    **[0039]**   In accordance with the principles of the present invention, there are mainly two modes  
13    of recording a signal onto tape 10. The same two modes also apply to the process of reproducing  
14    a signal from tape 10. The two modes are: a standard definition (SD) mode, used in the above  
15    description, and a standard definition long-play (SDL) mode. Included within the standard  
16    definition mode, there are two sub-types: standard play (SP) and long play (LP).

17    **[0040]**   The standard definition (SD) mode is used in a standard mode of the data recording or  
18    reproducing modes, in which heads A and B perform a normal recording or reproducing

operation.

[0041] The standard definition long-play (SDL) mode is used in a long-play mode of the data recording/reproducing modes, in which heads A and C perform the recording and reproducing operation. The signal recording and reproducing operation of the heads A and C of the SDL type is similar to the recording and reproducing operation of the heads A and B of the SD type. Accordingly, with the digital magnetic recorder and player having heads A, B, and C, as described above, the user can select SD and SDL types as she/he wishes when recording and reproducing signals.

[0042] It is possible to let head C remain unused during a recording operation in the standard definition (SD) mode, and just use heads A and B in the standard definition mode. However, I have discovered that a head C can be used advantageously during a recording operation in the standard definition (SD) mode, in accordance with the principles of the present invention. In the present invention, which is the subject of this patent application, the head C is used in the standard definition (SD) mode in order to notify a user of a faulty recording which is being performed, in accordance with the principles of the present invention. In other words, the present invention uses heads A, B, and C during a recording process when the standard definition (SD) mode of recording is performed. In an apparatus that can record in SD and SDL mode, there can be three heads, whereas heads A and B are used to record in SD mode, and heads A and C are used to record in SDL mode. Thus, in that apparatus, the head C would be unused during a

1 recording in SD mode. The present invention efficiently and advantageously utilizes the unused  
2 head C when recording in SD mode. The present invention uses head C to read data when a  
3 recording in SD mode is being performed.

4 [0043] FIGS. 3 and 4 show the structure of the magnetic tape 10. While the respective slant  
5 tracks 11 and 12 are actually slant at a predetermined angle with respect to the longitudinal  
6 direction of the magnetic tape 10, for an easier reference of readers, FIGS. 3 and 4 show the slant  
7 tracks 11 and 12 formed in a perpendicular relation with respect to a running direction of the  
8 magnetic tape 10.

9 [0044] The slant tracks 11 and 12 consist of first slant tracks 11 and second slant tracks 12,  
10 which are formed in alternate fashion with each other. The first and second slant tracks 11 and  
11 12 have different azimuth angles, *i.e.*, the first slant track 11 has the azimuth angle of  $\alpha$ , while  
12 the second slant track 12 has the azimuth angle of  $\beta$ . The azimuth angles  $\alpha$  and  $\beta$  of the first and  
13 second slant tracks 11 and 12 are opposite to each other, and accordingly, the recording  
14 directions of the first and second slant tracks 11 and 12 are different from each other. As  
15 described above, the head B corresponds to the first slant tracks 11, while the head A  
16 corresponds to the second slant tracks 12. The head A records data with an azimuth angle of  $a$ ,  
17 while the head B records data with the azimuth angle of  $b$ . Therefore, the head A only  
18 reproduces the signal from the second slant tracks 12, while the head B only reproduces the  
19 signal from the first slant tracks 11.

1     **[0045]**     Meanwhile, the heads C and B have the same azimuth angle. Accordingly, the heads B  
2     and C can reproduce signals from the same tracks, while they can not reproduce the signals  
3     recorded by the head A.

4     **[0046]**     Each of the first and second slant tracks 11 and 12 includes sub-code sectors 11a and  
5     12a, video sectors 11b and 12b, audio sectors 11c and 12c, and insert and track information (ITI)  
6     sectors 11d and 12d. The respective sectors 11a, 11b, 11c, 11d, 12a, 12b, 12c, and 12d are  
7     spaced from each other by a predetermined gap (g) in order to prevent interferences between the  
8     signals recorded thereon. The ITI sectors 11d and 12d store data such as Track Information, and  
9     the sub-code sectors 11a and 12a store data like date/time information, index information, track  
10    number, or the like. The video sectors 11b and 12b store data about image and its auxiliary data,  
11    while the audio sectors 11c and 12c store data about the sound and its auxiliary data. The size  
12    and order of data stored in the respective sectors 11a, 11b, 11c, 11d, 12a, 12b, 12c, and 12d are  
13    arranged in accordance with a predetermined format.

14   **[0047]**     FIG. 5 is a block diagram of a digital magnetic recorder/player having an apparatus for  
15    detecting abnormality of recorded signal according to the present invention, and FIG. 6 is a  
16    detailed block diagram showing the pre-amp shown in FIG. 5. The digital magnetic  
17    recorder/player according to the present invention includes a mechanic system 30 having a  
18    plurality of mechanical devices such as a motor for driving a cassette of magnetic tape 10 and a  
19    drum motor for driving the head drum 20, a servo control system 80 for the position control and

1 speed control of the mechanic system 30, a pre-amp 40 for amplifying the signal to be recorded  
2 onto the magnetic tape 10 or for amplifying the signal that has been reproduced from the  
3 magnetic tape 10, an equalizer system 50 for equalizing the signal to be recorded onto the  
4 magnetic tape 10 or for equalizing the signal that has been reproduced from the magnetic tape 10,  
5 an error checking and compressing system 55 for performing error check and data compression  
6 during the signal recording/reproducing operation, a shuffling and digital to analog (D/A) system  
7 60 for shuffling the data of the signal to be recorded onto the magnetic tape 10 or for shuffling  
8 the data of the signal that has been reproduced from the magnetic tape 10 and converting digital  
9 data to analog data, a video output driver system 70 for producing sound signals through proper  
10 devices such as an amplifier, or the like during playing operation, and a microcomputer (micom)  
11 90 for controlling overall recording/playing operation of the digital magnetic recorder/player.

12 [0048] As shown in FIG. 6, the pre-amp 40 includes three recording/reproducing amplifiers  
13 41, 42, and 43 for amplifying the signal to be recorded onto the magnetic tape 10 or for  
14 amplifying the signal that has been reproduced from the magnetic tape 10 during  
15 recording/reproducing of the heads A, B, and C, and a pre-amp control logic 45 for controlling  
16 the recording/reproducing amplifiers 41, 42, and 43. During a detection of an abnormality of  
17 recorded signal according to the present invention, the pre-amp 40 amplifies the signal to be  
18 recorded on the magnetic tape 10 and transmits the amplified signal to the heads A and B. The  
19 pre-amp 40 also amplifies the signal reproduced by the head C and transmits the amplified signal  
20 to the microcomputer 90. The pre-amp control logic 45 controls the respective



1 recording/reproducing amplifiers 41, 42, and 43 so that the head C can perform reproducing  
2 while the heads A and B perform recording.

3 [0049] In FIG. 6, pre-amp control logic 45 includes a first switch 100 and a second switch 102.  
4 the microcomputer 90 outputs switching pulses to pre-amp control logic 45. The switching  
5 pulses are shown in FIG. 7. The switching pulses can also be referred to as switching signals.  
6 When the first switch 100 is closed in response to the switching pulse, then the head A will  
7 record the input signal. When the first switch 100 is open in response to the switching pulse,  
8 then the head B will record the input signal. When the second switch 102 is closed in response to  
9 the switching pulse, then the head C will reproduce the recorded signal. The operation of the  
10 switches can be modified so that switch 100 is open in response to the switching pulse to cause  
11 head A to record the input signal, for example. Different terms can be used to describe the  
12 operating of the switches, of course. The switches can be opened/closed, activated/deactivated,  
13 turned on/turned off, for example.

14 [0050] FIG. 7 is a graph showing the switching timing of the respective heads A, B, and C  
15 which are controlled by the pre-amp control logic 45. As shown in FIG. 7, in a region where the  
16 switching pulse for the heads A and B is high, the head A performs recording operation, while in  
17 a region where the switching pulse is low, the head B performs recording operation. In a region  
18 where the switching pulse for the head C is high, the head C performs reproducing operation,  
19 while in a region where the switching pulse is low, the head C stops reproducing operation.

1 [0051] As shown in FIG. 7, the switching pulse for the heads A and B is switched to high or  
2 low in every 180° rotation of the head drum 20. Accordingly, during the rotation of the head  
3 drum 20, the heads A and B are activated alternately, and sequentially record signal on the  
4 second and first slant tracks 12 and 11 of the magnetic tape 10. The switching pulse for the head  
5 C is switched to high after a predetermined time from the beginning of the low pulse region of  
6 the switching pulse for the heads A and B. Here, the predetermined time corresponds to the 90°  
7 rotation of the head drum 20. The switching pulse for the head C is switched to high and low in  
8 every 180° rotation of the head drum 20.

9 [0052] FIGS. 8 to 11 show the variation of the position of the heads A, B, and C on the  
10 magnetic tape 10 when the heads A, B, and C are controlled as described above with reference to  
11 FIG. 7. The FIGS. 8 to 11 are similar to FIGS. 3 and 4, because FIGS. 8 to 11 also show the first  
12 and second slant tracks 11 and 12 in a perpendicular relation with respect to the running direction  
13 of the magnetic tape 10 for an easier reference of the readers. The FIGS. 8 to 11 identify the first  
14 slant track 11 with reference numeral 11(1), and identify the second slant track 12 with reference  
15 numeral 12(2).

16 [0053] FIG. 12 is a flow chart for explaining a method for detecting abnormality of recorded  
17 signal according to the first preferred embodiment of the present invention. At step S10, the  
18 inventive recording process is started by the digital magnetic recorder/player when the recording  
19 process is selected. The inventive recording process is the process for detecting the abnormality

1 of recorded signal during recording.

2 **[0054]** At step S10, the head drum 20 is rotated, and the head B is positioned at the end of the  
3 first slant track 11(1). This configuration is shown in FIG. 8. At step S20, the switching pulse of  
4 the heads A and B is switched to low, and the pre-amp control logic 45 drives the head B  
5 recording/reproducing amplifier 42, activating the recording operation of the head B. The  
6 switching pulse is shown in FIG. 7. The switching pulse can also be referred to as a switching  
7 signal. The pre-amp control logic 45 and the amplifier 42 are shown in FIG. 6.

8 **[0055]** The input signal to be recorded is input to pre-amp 40, the input signal is amplified by  
9 the pre-amp 42, and recorded on the first slant track 11(1) by the head B. The recording  
10 operation is maintained until the head B reaches the upper end of the first slant track 11(1).

11 **[0056]** The input signal to be recorded by heads A and B is shown to be inputted to pre-amp  
12 40 in FIG. 6. The input signal includes the information that is to be recorded onto the tape 10.  
13 That input signal can contain one or more of the following: video information, audio information,  
14 text data, formatting data, control data, numeric data, reference data, encryption data, auxiliary  
15 data, encoded data, other data.

16 **[0057]** At step S30, when the head B reaches the middle portion of the first slant track 11(1)  
17 during the recording operation of the head B, the head C reaches the lower end of the first track

1 11(1). This configuration is shown in FIG. 9. Also, at step S30, the pre-amp control logic 45  
2 starts reproducing operation of the head C by driving the head C recording/reproducing amplifier  
3 43. Since the width of the respective heads A, B, and C is wider than the width of the respective  
4 first and second tracks 11(1) and 12(2), the signal is recorded on the first slant track 11(1) and  
5 partially on the second slant track 12(2) next to the first slant track 11(1). The head C reproduces  
6 the signal recorded on the first slant track 11(1) and the second slant track 12(2).

7 [0058] As the head drum 20 keeps rotating, the head C reaches the middle portion of the first  
8 slant track 11(1) and the head A reaches the lower end of the second track 12(2). This  
9 configuration is shown in FIG. 10. In this situation, the pre-amp control logic 45 stops the  
10 recording of the head B, while recording signal on the second slant track 12(2) by driving the  
11 head A recording/reproducing amplifier 41. In other words, the pre-amp control logic 45 stops  
12 the recording operation performed by head B and starts a recording operation by head A.

13 [0059] As the head drum 20 keeps rotating, the head C reaches the upper end of the first slant  
14 track 11(1), and the head A is positioned on the middle portion of the second slant track 12(2).  
15 This configuration is shown in FIG. 11. In this situation, the pre-amp control logic 45 stops the  
16 reproducing operation of the head C. Next, the recording operation of the head A is maintained  
17 until the head A reaches the upper end of the second slant track 12(2).

18 [0060] When the head A reaches the upper end of the second slant track 12(2), the head B

1 reaches the lower end of the first slant track 11 next to the second slant track 12(2), and the head  
2 B re-starts recording operation. By repeating the above processes, the recording operation is  
3 continuously performed by the heads A and B, while the head C reproduces the signal recorded  
4 by the head B after a predetermined time period.

5 **[0061]** In this embodiment, there is a slight time delay between the time that head B records  
6 data onto the tape 10 and the time that head C reproduces that recorded data. This is true because  
7 head C is separately located from head B on the drum 20. Thus, a particular track of tape 10 will  
8 be adjacent to head B before that particular track of tape 10 is adjacent to head C. This is  
9 consistent with the switching pulses shown in FIG. 7, which show a 90° difference between the  
10 beginning of the recording performed by head B and the beginning of the reading by head C. In  
11 this embodiment, there is a 90° angle formed at drum 20 between the locations of head B and  
12 head C. It is possible to locate heads B and C on drum 20 in other configurations. For example,  
13 it is not necessary that a 90° angle formed at drum 20 between the locations of head B and head  
14 C. An angle greater than 90° or an angle less than 90° could be used.

15 **[0062]** Meanwhile, the signal reproduced by the head C is inputted to the microcomputer 90  
16 through the pre-amp 43. At step S40, based on the signal reproduced by the head C, the  
17 microcomputer 90 determines whether the recording is being normally performed or not.  
18 Determining abnormality of recorded signal of the recorder/player by using signal reproduced by  
19 the head C can be performed in many ways. For illustrative purposes, described below are some

1 methods of determining abnormality of recorded signals, in accordance with the principles of the  
2 present invention. The microcomputer 90 can use a comparator function to compare the signals  
3 in order to detect abnormalities.

4 **[0063]** One demonstrative example of the actions that occur within step S40 is as follows. The  
5 step S40 can correspond to a comparison of data. That is, in step S40, a reference signal can be  
6 compared to the signal reproduced by head C. If the reference signal and the signal from head C  
7 are substantially equal, then it is deemed that no abnormalities are present, and thus the user is  
8 not notified that errors have occurred. However, if the reference signal and the signal from head  
9 C are not substantially equal, then it is deemed that abnormalities are present, and thus the user is  
10 notified that errors have occurred.

11 **[0064]** As described above, based on the data of the signal reproduced from the magnetic tape  
12 10 by the head C, the microcomputer 90 determines whether the format of the whole or a part of  
13 the data corresponds to the normal format, and accordingly determines whether there is an  
14 abnormality in the signal recorded by the head B. In step S40, when the microcomputer 90  
15 determines the recording is normally performed by the head B, then step S50 is performed next.  
16 At step S50, the head A performs recording. Then, at step S60, a determination is made as to  
17 whether recording is finished. Until the recording is finished, the recording, the reproducing, and  
18 the recorded signal abnormality detections are continuously performed (steps S20 to S40).

1     **[0065]**     In step S40, if the microcomputer 90 determines abnormality of the signal recorded by  
2     the head B, then the step S70 is performed next. At step S70, the microcomputer 90 indicates  
3     abnormal status on a display (not shown) of the digital magnetic recorder/player. Accordingly,  
4     the user is notified of the abnormality of the signal, and accordingly deals with the problem such  
5     as stopping the recording, having the apparatus repaired, eliminating the foreign substances from  
6     the head, or the like. The user can be notified of the abnormality by a sound such as an audio  
7     alarm, by a light, by information displayed on a display including text and/or images, or the user  
8     can be notified by any combination of sound, light, and information.

9     **[0066]**     The microcomputer 90 can detect an abnormality in a recorded signal of the  
10    recorder/player using many different methods. One method that microcomputer 90 can use, for  
11    example, to determine that a recorded signal is abnormal, is to compare the data format of the  
12    data reproduced from the tape 10 with a predetermined data format. As described above, data  
13    can be stored in the respective sectors 11a to 11d of the first slant track 11(1), in accordance with  
14    a predetermined data format, and the microcomputer 90 can be provided with information about  
15    the predetermined data format. The microcomputer 90 can receive the data format which is  
16    reproduced using head C, and then compare that received data format with the predetermined  
17    data format.

18   **[0067]**     The predetermined data format information can be any one of many different types of  
19    information. The predetermined data format information can be one or more types of

1 information. For example, the predetermined data format can correspond to a synchronization  
2 information, identification (ID) information, date-related information, time-related information,  
3 index-related information, structure-related information, or another type of information. The  
4 predetermined data format can correspond to any predetermined information.

5 **[0068]** Please turn now to FIG. 14, which is a diagram for explaining the comparison  
6 performed by a microcomputer to determine if abnormalities exist in a recorded signal, in  
7 accordance with the principles of the present invention. Head C reproduces a recorded signal  
8 from tape 10. The reproduced signal is then conveyed from head C to error check and compress  
9 system 55 for processing and then to microcomputer 90. The processing performed by error  
10 check and compress system 55 is shown in more detail in FIG. 15. The data reproduced by head  
11 C can be conveyed to other units, in addition to units 55 and 90, but FIG. 14 has simplified the  
12 process for illustrative purposes.

13 **[0069]** In FIG. 14, the signal reproduced by head C is conveyed to unit 55 for processing and  
14 then to microcomputer 90. The microcomputer 90 also receives predetermined data format  
15 information stored in memory 104. The memory 104 can be an internal memory of  
16 microcomputer 90 or can be an external memory. The memory 104 either is contained within  
17 microcomputer 90 or is connected to microcomputer 90. The microcomputer compares the data  
18 from unit 55 with the data stored in the memory 104. If a number of differences exceeding a  
19 preset threshold are detected, then the microcomputer 90 determines that abnormalities exist and



1 outputs a signal indicating that abnormalities exist to notify a user. If a particular type of  
2 differences is detected, then the microcomputer 90 determines that abnormalities exist and  
3 outputs an appropriate signal to notify a user.

4 [0070] One example of the process shown in FIG. 14 is as follows. Let us say that a family is  
5 making a home movie for their relatives. The home movie is being made on 10 January 2001. If  
6 the predetermined data format includes date information, then the memory 104 of the inventive  
7 apparatus stores the current date which is 10 January 2001. The family begins to videotape a  
8 picnic, and head B records the data onto tape 10. The head B records the current date and time  
9 onto the tape 10 by head B, in addition to the video images of the family having a picnic. Very  
10 soon after tape B records the data on tape 10, the head C reproduces that recorded information  
11 and conveys that information to microcomputer 90. The microcomputer 90 compares the  
12 predetermined data received from the memory 104 with the reproduced information received  
13 from unit 55. The memory 104 has stored the current date 10 January 2001. If there are no  
14 abnormalities, the date in the reproduced information will be the same as the date stored in the  
15 memory 104. Thus, the user will not be notified that there are abnormalities. However, if the  
16 reproduced information contains a date that is not 10 January 2001, or does not contain any date,  
17 or contains corrupted or invalid information, then an abnormality is detected, and so the user will  
18 be promptly notified that the abnormality is present. The notification to the user could be in the  
19 form of one or more of the following: a beep or other sound, a flashing or constant light, an  
20 image or a text message being displayed, a vibration of the apparatus, or by some other means

1 whereby the user is alerted to the fact that an abnormality exists. The abnormality may exist for  
2 many different reasons. The abnormality may be caused by dirt on the head B, for example. Or  
3 the abnormality could be the result of a poorly manufactured tape 10, or an excessively used tape  
4 10, or a tape 10 that has been exposed to very high temperatures, or by dirt on the tape 10.  
5 Presuming a user is attempting to record onto a tape that is damaged because the tape has been  
6 previously exposed to very high temperatures, this is what might happen: first, the user puts the  
7 damaged tape into the apparatus and begins to tape the family picnic. The user is immediately  
8 notified that an abnormality exists, because the data in memory 104 does not match the data in  
9 the reproduced signal. The user is now aware that a problem exists. The user throws away the  
10 damaged tape and puts a brand new tape in the apparatus, and begins recording the picnic again.  
11 Now the data in memory 104 matches the data in the reproduced signal, and there are no  
12 abnormalities.

13 [0071] In this manner, the apparatus of the present invention promptly notified the user that  
14 abnormalities existed in the recording of the picnic. If the user was unfortunate enough to be  
15 using an apparatus that did not have the advantages of the present invention, the user might have  
16 spent the entire afternoon having a picnic with the family and taping the picnic. Then, later that  
17 day or later that week, the user would attempt to view the tape. Only then would the user realize  
18 that there were errors. The user might be frustrated and dissatisfied. The user had spent time and  
19 effort taping the picnic and had basically wasted a lot of time and effort. The user had expected  
20 to be able to send the tape to the relatives. But the abnormalities were so severe that the

1 recording of the picnic was unintelligible. The relatives would be disappointed, because they  
2 were expecting to see the tape.

3 [0072] The present invention allows the user to immediately be made aware of abnormalities  
4 in the recording. Thus, the user can try to use a different tape, or the user can use a different  
5 apparatus, or the user can use a cleaning device to clean the heads. The advantage of the present  
6 invention is that the user is promptly alerted to the fact that a problem exists. The user does not  
7 need to waste a lot of time and effort recording information, only to learn later that all that time  
8 and effort was utterly wasted.

9 [0073] Also, the present invention is efficient and sophisticated. No additional heads need to  
10 be added to the device. Heads A, B, and C are already there. The present invention uses head C  
11 to detect errors in the standard definition (SD) mode. As was stated previously, heads A and B  
12 are used in SD mode, whereas head C is not needed, in a related art. Thus, by utilizing a  
13 previously unused head C in the detection of abnormalities, the inventor has efficiently and  
14 elegantly added important and useful functions to a recording apparatus. No additional heads  
15 need to be added to utilize the apparatus and method of the present invention.

16 [0074] Also, the present invention is advantageous because the present invention does not stop  
17 recording in order to read the recorded signal. Thus, the head B is able to constantly record the  
18 input signal, and the head C is able to constantly reproduce the recorded signal. This is an

1 efficient design. A less efficient design might need to stop recording the signal in order to  
2 reproduce the recorded signal. The present invention is advantageous over the aforementioned  
3 less efficient design. The useful life of an apparatus can be shortened by excessive starting and  
4 stopping. Additional control signals are needed for excessive starting and stopping. Battery life  
5 can be reduced due to excessive starting and stopping. Power consumption can increase in an  
6 undesirable way due to excessive starting and stopping.

7 **[0075]** In addition, the head C of the present invention will read data from the same track that  
8 was most recently written to. In other words, head B records data to track 11(1) of tape 10 and  
9 then head C promptly reproduces that data from track 11(1). This allows the user to be promptly  
10 notified of abnormalities, and is also advantageous for reasons of efficiency and design. These  
11 features are illustrated in FIGS. 8 to 11, which show head B writing to track 11(1) and then head  
12 C reproducing data that was recorded on track 11(1).

13 **[0076]** The predetermined data stored in memory 104 can be any one (or more) of many  
14 different types of information, as described above. The date is one example. Synchronizing data  
15 is another example. Other header-type information is another example. Standard reference data  
16 is another example. A combination of different types of information can be used for the  
17 predetermined data stored in memory 104.

18 **[0077]** For example, for normal recording operation, the number of bits of the data reproduced

1 from the magnetic tape 10 will correspond to the number of bits of the data stored in the  
2 respective sectors 11a to 11d. In addition to the above-mentioned way of determining  
3 abnormality of recorded signal of the recorder/player, the recorded signal abnormality detection  
4 can also be accomplished by using the fact that the sub-code sector 11a stores information about  
5 date and time. That is, the abnormality of recorded data can be detected either by determining  
6 whether the signal reproduced from the magnetic tape 10 contains information about the date and  
7 time, or by determining whether the insert and track information (ITI) sector 11d stores  
8 information about the tracks.

9 **[0078]** FIG. 13 is a flow chart for explaining a method for detecting abnormality of recorded  
10 signal according to second preferred embodiment of the present invention. In this embodiment,  
11 the steps of selecting recording operation (S110), recording by the head B (S120), reading by the  
12 head C (S130), recording by the head A (S150), determining if recording is finished (S160), and  
13 displaying malfunction (S170) are similar to the corresponding steps described above in the  
14 description of the first embodiment, with reference to steps 10, 20, 30, 50, 60, and 70 of FIG. 12,  
15 respectively.

16 **[0079]** The method of detecting an abnormality in a recorded signal as illustrated in FIG. 13 is  
17 different from the method of detecting an abnormality in a recorded signal as illustrated in FIG.  
18 12. The step S40 in FIG. 12 is not the same as the step S140 in FIG. 13. Accordingly, the step  
19 S140 of detecting abnormality of recorded signal, which is the unique feature of the second

embodiment, will now be described below in greater detail.

[0080] The step S140 of FIG. 13 includes the substeps S141 and S142. At step S141, an envelope is generated of the signal reproduced by head C. At step S142, the voltage level of the envelope is compared with a reference voltage level. If the voltage level of the envelope is greater than or equal to the reference voltage level, then the microcomputer 90 determines that no abnormalities exist and then head A records data at step S150. Otherwise, step S170 is performed to alert a user to an abnormality in the recording operation.

[0081] Immediately after the recording by the head B, the signal reproduced by the head C is inputted to the microcomputer 90 via the pre-amp 43. The microcomputer 90 generates an envelope of the signal reproduced by the head C (step S141). The envelope can be easily generated by proper methods such as a digital to analog (D/A) conversion that converts digital signal reproduced by the head C into analog signal. By comparing the signal level of the envelope with a reference signal level, the microcomputer 90 determines whether there is an abnormality of recorded signal (step S142). For example, when the voltage level of the envelope is greater than the reference voltage level, the microcomputer 90 determines that there is no abnormality of recorded signal. Meanwhile, when the voltage level of the envelope is less than the reference voltage level, the microcomputer 90 determines there is an abnormality in the recorded signal. A voltage level usually obtained from the signal normally recorded on the magnetic tape 10 by the head B can be tentatively set as a reference signal level.

1     **[0082]**   Please turn to FIG. 15, which shows         a diagram for explaining the function of the  
2     error check and compress system 55, in accordance with the principles of the present invention.  
3     The unit 55 includes units 106, 108, 110, and 112.

4     **[0083]**   When the inventive apparatus is recording data to the tape 10, then the units 106 and  
5     108 are utilized. Unit 106 serves to perform processing for modulating, compressing, and  
6     arranging the data to be recorded. Unit 108 serves to transmit the modulated, compressed, and  
7     arranged data to the equalizer 50. The equalizer 50 will equalize the data and then transmit the  
8     equalized data to the pre-amp 40 for preamplification. Then the data will be transmitted to the  
9     heads so that the data can be recorded onto the tape 10.

10    **[0084]**   When the inventive apparatus is reproducing data from the tape 10, then the units 110  
11    and 112 are utilized. Unit 110 serves to perform processing for demodulating, expanding, and  
12    rearranging the data to be reproduced. Unit 112 serves to transmit the demodulated, expanded,  
13    and rearranged data to the microcomputer 90. The microcomputer will then perform the  
14    comparisons to detect abnormalities, as described above.

15    **[0085]**   With reference to FIG. 5, data shall be transmitted from unit 55 to unit 40 and then to  
16    unit 30 when the present invention is in a write mode or recording mode. Data shall be  
17    transmitted from unit 30 to unit 40 to unit 50 and then to unit 55 when the present invention is in  
18    a read mode or reproducing mode.

1     **[0086]**     As described above, the preferred embodiments of the present invention use the head  
2     C, which is used in the long-play mode of the SDL type recorder/player, to detect the abnormality  
3     of the recorded signal. That is, in the digital magnetic recorder/player which can be operated  
4     both according to the SD type and SDL type, the head C, which is not used especially according  
5     to the SD type apparatus, is used to detect the abnormality of the recorded signal. Accordingly,  
6     without having to employ an additional recording/reproducing head, the abnormality of the  
7     recorded signal can be detected by the head C which is installed in the general digital magnetic  
8     recorder/player.

9     **[0087]**     Also, in the digital magnetic recorder/player which is not provided with all of the three  
10    heads A, B, and C, the method for detecting abnormality of the recorded signal according to the  
11    present invention still can be applied by adding a separate reproducing head.

12   **[0088]**     The preferred embodiments of the present invention show the case where only the  
13    abnormality of signal recorded by the head B is detected by reproducing signal recorded by the  
14    head B. However, since the foreign substance, which can be the main cause of the malfunction  
15    of the head, is attached on the heads when the heads are used or exposed in the air for a long  
16    period of time, the presence of foreign substances on one head (head B) means the same situation  
17    at the other heads which have been used or exposed in the air for the same period of time as the  
18    head A. Accordingly, the result obtained after detecting abnormality of the signal recorded by  
19    the head B can sufficiently show the abnormality of the recorded signal of the digital magnetic



recorder/player.

[0089] According to the present invention as described above, an abnormality of recorded signal, which is caused due to the presence of the foreign substances or from other problem sources, can be detected either by A) reproducing the signal which is recorded on the magnetic tape 10 and checking the data format of the signal, or by B) comparing the voltage level of an envelope of recorded signals with a reference voltage level. Accordingly, the user has a convenience since she/he is notified of the abnormality of recorded signal while performing recording. Further, since a head for long play mode, which is not used in the standard mode, is used to detect the abnormality of the recorded signal, the abnormality detection can be easily performed without having to employ an additional recording head.

[0090] The foregoing paragraphs describe the details of an apparatus and method for detecting an abnormality of a recorded signal of a digital magnetic recorder/player, and more particularly, describe the details of an apparatus and method for detecting an abnormality of a recorded signal during a recording on a magnetic tape, which is occurred when the signal is abnormally recorded due to foreign substances attached to a head or from other problem sources.

[0091] The present invention can be applied to digital video cassette (DVC) units, other types of video recording units, audio recorders. In addition, the present invention can be used in conjunction with media other than the digital magnetic tape 10 described above. For example,

1 other media, such as the media used by computers, including a hard disk drive used by a  
2 computer and a removable medium used by a computer, and the like, can be used in conjunction  
3 with the principles of the present invention. The present invention can be applied to magnetic  
4 media such as magnetic tape, disks used in hard disk drives, disks used in other drives, and the  
5 like. The present invention can also be applied to optical media such as a factory pressed  
6 compact disk (CD), a compact disk-recordable (CD-R), a compact disk-rewriteable (CD-RW),  
7 laser disks, and other optical media.

8 [0092] The detected abnormality in the recorded signal can be caused by a presence of  
9 contamination on a head, by a presence of foreign substances on a head, by a presence of  
10 contamination on a medium, by a poorly manufactured medium, by an excessively used medium,  
11 by an unstable power supply, or by other problem sources.

12 [0093] In accordance with the principles of the present invention, a head C reads data that was  
13 written by head B, and then a determination is made as to whether there are abnormalities or  
14 irregularities or problems with the data written by head B. The use of head C to reproduce a  
15 recorded signal, in accordance with the principles of the present invention, need not be limited to  
16 a standard definition (SD) mode. The head C can be used in modes different from the standard  
17 definition (SD) mode, in accordance with the principles of the present invention.

18 [0094] As described above, in a recording operation in the standard definition long play (SDL)

1 mode, the heads A and C are used to record information on tape 10, while head B is unused. A  
2 particular track of tape 10 will be adjacent to head B before that particular track is adjacent to  
3 head C, in accordance with the direction of rotation of drum 20 and the direction of travel of tape  
4 10 shown in FIG. 1. When a record operation is performed in standard definition long play  
5 (SDL) mode, information previously recorded on the tape 10 can be read from the tape 10 using  
6 head B immediately prior to the head C writing new information onto the tape 10. The  
7 information read by head B can then be written to another medium or otherwise transmitted.  
8 Thus, the previously written information on tape 10 can be stored before it is overwritten by the  
9 information being written by head C. This technique is fast, convenient, and efficient, because  
10 two tasks can be accomplished at once. That is, first information can be read from tape 10 (using  
11 head B) and then second information can be written to tape 10 (using heads A and C) all in one  
12 operation, without any need to stop rotation of the tape 10.

13 [0095] While the present invention has been illustrated by the description of embodiments  
14 thereof, and while the embodiments have been described in considerable detail, it is not the  
15 intention of the applicant to restrict or in any way limit the scope of the appended claims to such  
16 detail. Additional advantages and modifications will readily appear to those skilled in the art.  
17 Therefore, the invention in its broader aspects is not limited to the specific details, representative  
18 apparatus and method, and illustrative examples shown and described. Accordingly, departures  
19 may be made from such details without departing from the spirit or scope of the applicant's  
20 general inventive concept.